

B & W; DM-580; passief;
 Systeem: basreflex; Aantal speakers: 3; Impedantie: 8 Ohm; Rendement 1W/1M: 91 dB; Belastbaarheid continue: 150 Watt; Frequentiebereik: 38 Hz-30 KHz; Bescherming tegen overbelasting: ja; Type en omschrijving drivers; Laag: 200 mm Fiber conus; Midden: 200 mm Fiber conus; Hoog: 26 mm metal dome; Afmetingen (hxbxd): 236x886x407; Uitvoeringen: zwart/noten; Winkelprijs: f. 749,- per stuk.

Ver. v. Historie v/d Radio



ITEM	Code N°	Component	Value	Remarks
-	ZZ4189			COMPLETE CROSSOVER ASSEMBLY (drg. A1486/1)
C1	C1031	CAPACITOR	5.3 μ F	electrolytic reversible 70V \pm 5%
C3	C0159	CAPACITOR	8 μ F	electrolytic reversible 70V \pm 5%
C4	C1287	CAPACITOR	7 μ F	electrolytic reversible 70V \pm 5%
L1	ZL0906	INDUCTOR	65 mH	0.90 wire + core
L2	ZL0310	INDUCTOR	1.3 mH	0.71 wire + core
L3	ZL0175	INDUCTOR	0.2 mH	0.45 wire
	F0795	FUSE	2.0 Amp	20 x 5mm Q.B.
	W1023	WIRE		Black 16/0.2 x 60mm x 2 off
	T0736	EYELETT		TUCKER 4.2 I/D x 2 off
	C6513	CABLE TIE		2 off
P.C.B.	C4529			Printed Circuit Board - DM580