



CONNECTIONS TO CHASSIS INDICATED THUS

CIRCUIT DIAGRAM—BUSH MODELS SUG.3 AND DUG.3

**Capacitors.**

C1	0.005
C2	800 pF.
C3	0.005
C4	50 pF.
C5	0.05
C6	30 pF.
C7	0.05
C8	110 pF.
C9	0.05
C10	110 pF.
C11	50 pF.
C12	180 pF.
C13	390 pF.
C14	556 pF.
C15	0.05
C16	0.05
C17	0.1
C18	0.05
C19	110 pF.
C20	0.01
C21	0.01
C22	100 pF.
C23	2
C24	0.1
C25	0.05
C26	110 pF.
C27	50 pF.
C28	50
C29	0.001
C30	0.01
C31	0.05
C32	0.01
C33	0.001
C34	16.
C35	32
C36	0.1

**Resistors.**

R1	15k
R2	1M
R3	100
R4	33k
R5	2.2M
R6	220
R7	47k
R8	47k
R9	220
R10	47k
R11	10k
R12	330k
R13	4700
R14	100k
R15	2200
R16	68k
R17	4700
R18	1000
R19	1M
R20	470k
R21	47k
R22	10k
R23	150
R24	3300
R25	150
R26	600 + 100 + 100

VR1	2M
VR2	50k

**Variable Capacitors.**  
 VC1 } 2 x 533 pF.  
 VC2 } Ganged  
 TC1-TC6 } 3-40 pF.

Met dank aan Arie Schets