



THE SHAFT END IN THEIR EXTREME COUNTERCLOCKWISE POSITIONS.

- NOTES:
1. ALL RESISTORS ARE 1/2W, 10% UNLESS OTHERWISE SPECIFIED. ALL RESISTANCE VALUES ARE IN OHMS.
 2. ALL CAPACITANCE VALUES ARE IN UF UNLESS OTHERWISE SPECIFIED.
 3. SWITCHES ARE SHOWN VIEWED FROM

SCHEMATIC DIAGRAM

PARTS LIST

SYM. #	STOCK#	DESCRIPTION	SYM#.	STOCK#	DESCRIPTION
<u>CAPACITORS</u>					
C1, 2	22556	disc, 68uuf, 500V	R8	10438	330Ω
C3	22550	disc, 600uuf, 500V	R9	10857	2200Ω, 1W
C4, 5, 6, 7, 15, 20	22533	disc, 47uuf	R10, 31, 43	10436	47Ω
C17	22551	disc, 22uuf	R11, 12	10400	10KΩ
C8, 11, 28	22515	disc, 500uuf	R13	10851	22KΩ, 1W
C9	29006	tuning, sweep	R14	10418	4.7MΩ
C10	24001	elect., 2 x 20ufd, 450V	R15	10407	1MΩ
C12	20501	tubular, 2ufd, 150V	R16	14309	7000Ω, 10W
C13	20056	tubular, 1ufd, 200V	R17	18017	potentiometer, 2MΩ
C14	22522	disc, 330uuf, 500V	R18	10849	47KΩ, 1W
C16	22503	disc, .01, 1500V	R20	10844	330KΩ, 1W
C22, 30,	22521	disc, .001ufd, 500V	R21	10446	270Ω
C18, 21	22023	tubular, 2uuf	R22	18112	potentiometer, 100KΩ
C19	29007	tuning, marker	R23, 32, 33, 34	10429	470Ω
C23, 29	22528	disc, 2 x .005ufd	R24, 42	10428	47KΩ
C24	22526	disc, .005ufd	R26	10424	22KΩ
C25	20067	tubular, .25ufd, 200V	R27	18115	potentiometer, 200Ω
C26	23010	elect., 10ufd, 150V	R28, 29, 30	10437	56Ω
C27	23015	elect., 50ufd, 150V	R36	10450	3900Ω
C31	20026	tubular, .047ufd, 600V	R37	10855	4700Ω, 1W
<u>COILS</u>			R38	10426	33KΩ
L1	36011	variable	R39	10956	10KΩ, 2W
L2	36012	variable	R40	10852	15KΩ, 1W
L3	36013	variable	R41	18114	potentiometer, 10KΩ
L4	35021	25uh, plain core	<u>SWITCHES</u>		
L5	37010	controllable inductor	S1	60122	rotary, marker
L6	35052	100uh, plain core - 3 pi	S2	60123	rotary, attenuator
L7, 8	35020	25uh, iron core	S3	60124	rotary, range
<u>RESISTORS</u>			S4	18111	ON-OFF on R1
(All resistors are 1/2 watt, 10% unless noted otherwise)			<u>TUBES</u>		
R1	18111	potentiometer, 2MΩ, w/SPST	V1	90013	12AU7
R2, 19, 35	10410	100KΩ	V2	90052	6BQ7A
R3, 6	10412	330KΩ	V3	90034	12AX7
R4	18113	potentiometer, 100KΩ	V4	90088	6DR7
R5	10406	680Ω	V5	90012	12AT7
R7, 25	10430	4700Ω	V6	90036	6X4

JUL 2 1 1968

MODEL 369-1 OPERATING MANUAL ADDENDUM

Please make the following additions to your Operating Manual:

Parts List:

Add C32 22521 disc .001ufd, 10% Z5U

Schematic:

Add a .001ufd, C32 Capacitor across pins 4 and 5 of Tube 6BQ7A