



Met dank aan Leo Smits

TABLE OF COMPONENTS

A46

CODE	VALUE	SQUARE	TEST		CODE	VALUE	SQUARE	TEST		CODE	VALUE	SQUARE	TEST	
			From	To				From	To				From	To
C1a	Variable	18 K	6	11	C42	4 μ F (+00v.)	1 D	11	58	L3	10	13 D	4	11
C1b	Variable	18 L	11	12	C43	0.025 μ F	4 G	56	59	L4	—	13 B	9	13
C1c	Variable	18 N	11	37		(RG) 0.003 μ F				L6	4	13 D	9	14
C2	Trimmer	16 K	11	14	C44	0.04 μ F	3 E	64	66	L7	12	13 D	9	16
C3	50pf	14 D	8	9	C45	50 μ F (12v.)	5 F	61	63	L8	4	13 D	7	9
C4	62pf	13 C	9	16	C46	8 μ F (+00v.)				L9	12	14 D	8	9
C6	Trimmer	18 K	6	11	C47	(RG) 16 μ F	1 D	11	72	L11	—	13 O	27	28
C7	Trimmer	18 L	11	12						L12	1.5	13 G	26	27
C8	0.1 μ F	12 C	9	11						L13	—	13 G	11	33
C9	0.025 μ F	10 H	17	18	R1	15,000	11 F	18	29	L14	2.5	13 G	11	34
C11	0.05 μ F	11 O	11	17	R2	33,000	10 G	20	21	L16	4	13 O	11	36
C12	200pf	13 F	11	27	R4	300	14 G	11	17	L17	6	22 S	18	19
C13	100pf	12 D	21	32	R6	100	10 F	22	23	L18	6	22 S	9	42
C15	35pf	20 T	11	34	R7	1,000	13 H	24	26	L19	6	25 R	29	44
C16	Trimmer	16 P	11	33	R8	20,000	14 F	17	27	L21	6	25 S	53	57
C17	Trimmer	16 O	11	34	R9	450	9 E	11	41	L24	1400	L.S. Field	29	72
C18	2+5pf	14 G	11	36	R10	100,000		11	43					
C19	Trimmer	16 J	11	36	R11	2 M Ω	9 C	9	57					
C22	703pf	10 E	34	38	R12	100,000	25 S	51	57	T1 prim				
C23	386pf	10 E	36	39	R13	500,000	25 S	51	52	200-213v	26		78	84
C24	Trimmer	21 P	18	19	R14	500	8 C	11	52	214-228v	28		79	84
C26	125pf	22 T	18	19	R16	50,000	26 L	49	54	229-244v	31		81	84
C27	134pf	22 S	9	42	R17	50,000	4 F	56	58	245-260v	33	26 O	82	84
C28	Trimmer	21 P	9	42	R18	15,000	3 F	29	58	H.T. sec.				
C29	8 μ F (+00v.)	1 D	11	29	R19	1 M Ω	27 L	11	46		210		11	73
C31	Trimmer	21 L	29	44	R21	25,000	6 A	29	66		+240		11	74
C32	125pf	25 T	29	44	R22	50,000	5 G	59	62					
C33	125pf	25 S	53	57	R23	210	4 G	11	61					
C34	Trimmer	20 L	53	57	R24	500,000	4 G	11	59	T2 prim	140	ON	29	64
C36	0.025 μ F	8 E	11	41						T2 sec		L.S.	11	68
C37	0.01 μ F	25 R	47	51										
C38	100pf	25 R	52	57	L1	—	13 B	2	11	L.S.	2		11	71
C39	100pf	25 S	51	52	L2	1.25	13 D	3	11	Sp. coil				